





Adapteur droit Mâle BSP pour bague BS X Mâle cloison BSP pour bague BS + Contre-Ecrou

S MBSPBS X MBHBSPBS + LN

PT148	BSPBS (E)	BSPBS (F)	L1	L2	LL	d1	d2	H	H2	
1AP14100	G1/8-28f	G1/8-28f	10	33	49	3,5	3,5	14	14	
1AP17050	G1/4-19f	G1/4-19f	12	35	53	4,7	4,7	19	19	
1AP21050	G3/8-19f	G3/8-19f	13,5	35	56,5	7,9	7,9	22	22	
1AP27050	G1/2-14f	G1/2-14f	16	39	65	11,1	11,1	27	27	
1AP28100	G5/8-14f	G5/8-14f	17,5	40	67,5	14,3	14,3	30	30	
1AP32050	G3/4-14f	G3/4-14f	18,5	42	71,5	16,7	16,7	32	32	
1AP42050	G1"-11f	G1"-11f	20,5	50	84	22,2	22,2	41	41	
1AP50050	G1"1/4-11f	G1"1/4-11f	20,5	52	89,5	28,6	28,6	50	50	
1AP54100	G1"1/2-11f	G1"1/2-11f	23	55	93	33,3	33,3	55	55	
1AP70100	G2"-11f	G2"-11f	25,5	55	97,5	46	46	70	70	

Pression majorée avec cône BSP

Adapteur droit Mâle cloison ORFS + Contre-Ecrou X Mâle BSP Forme E

S MBHORFS + LN X MBSPE

PT293	ORFS (E)	BSPE (F)	L1	L2	LL	d1	d2	H	H1	
1FS63002	13/16-16f	G1/4-19f	41	12	59,5	9,5	5	30	30	
1FS63004	9/16-18f	G3/8-19f	31,5	12	54	4,5	8	22	22	
1FS63006	11/16-16f	G3/8-19f	34	12	57,5	6,5	8	27	27	
1FS63008	13/16-16f	G1/2-14f	36,5	14	62,5	9,5	12	30	30	
1FS63010	1"-14f	G1/2-14f	40,6	14	68	12	12	36	36	
1FS63011	1"3/16-12f	G5/8-14f	41,7	16	71	14	14	41	41	
1FS63012	1"3/16-12f	G3/4-14f	41,7	16	71	15,5	15,5	41	41	
1FS63016	1"7/16-12f	G1"-11f	42,2	18	75,5	20	20	46	46	