



Adapteur droit Mâle BSP X Corps de Banjo

S MBSP X BAJCP

PT222	BSP (E)	BAJCP (F)	L	LL	D					
1DA99010	G1/8-28f	1/8	12	20	3.5					
1DA99012	G1/4-19f	1/4	14	25	4.7					
1DA99016	G3/8-19f	3/8	17	29	7.9					
1DA99020	G1/2-14f	1/2	22	35	11.1					
1DA99024	G3/4-14f	3/4	28	38	16.7					

Adapteur droit Mâle GAZ Conique X Queue Cannelée

S MR X HOSN

PT264	R (E)	HOSN (D2)	L1	L2	LL	d1	d2	H	FORME	
1QG14050	R1/8-28f	6	10	25	41	4,5	4,5	12	W	
1QG14060	R1/4-19f	6	14	25	45	7	4,5	14	W	
1QG17070	R1/4-19f	8	14	26	47	6	6	14	W	
1QG14080	R1/4-19f	10	14	32	52	7	7	14	W	
1QG17090	R1/4-19f	13	14	34	55	7	10	17	W	
1QG17110	R3/8-19f	6	15	25	47	10	4,5	17	W	
1QG19100	R3/8-19f	8	15	26	48	10	6	17	W	
1QG17100	R3/8-19f	10	15	32	54	10	8	17	W	
1QG19120	R3/8-19f	13	15	34	56	10	10	17	W	
1QG19130	R3/8-19f	16	15	38	60	10	13	19	W	
1QG22140	R1/2-14f	12,5	19	34	61	13	10	22	W	
1QG22150	R1/2-14f	16	19	38	65	13	13	22	W	
1QG22160	R1/2-14f	19	19	41	68	13	16	22	W	
1QG27140	R3/4-14f	13	27,1	34	63	18	10	27	W	
1QG30170	R3/4-14f	16	20	38	67	18	13	27	W	
1QG30180	R3/4-14f	19	20	41	70	18	16	27	W	
1QG30190	R3/4-14f	25	20	45	74	18	21	27	W	
1QG36200	R1"-11f	25	24	45	79	24	21	36	W	
1QG36210	R1"-11f	32	24	48	82	24	28	36	W	
1QG46210	R1"1/4-11f	32	25	48	85	31	28	46	W	
1QG45200	R1"1/4-11f	39	25	53	90	31	31	46	W	
1QG50220	R1"1/4-11f	32	25	48	85	38	28	50	W	
1QG50230	R1"1/2-11f	38	25	53	90	33	33	50	W	
1QG63240	R2"-11f	50	30	66	111	44	44	65	W	
1QG77250	R2"1/2-11f	63,5	36	85	141	56	56	80	W	

Seule la partie GAZ conique est prise en compte