







# Raccords d'implantation




## FBPL Raccord droit, mâle NPT

	Laiton nickelé 	<b>ØD</b>	<b>C</b>		<b>F</b>	<b>F1</b>	<b>H</b>	<b>kg</b>
		2,7x4	NPT1/8	<a href="#">FBPL2.7/4-1/8</a>	11	8	22	0,011
		4x6	NPT1/8	<a href="#">FBPL4/6-1/8</a>	11	11	25	0,016
		4x6	NPT1/4	<a href="#">FBPL4/6-1/4aV</a>	11	11	29	0,026
		6x8	NPT1/8	<a href="#">FBPL6/8-1/8</a>	14	13	25	0,016
		6x8	NPT1/4	<a href="#">FBPL6/8-1/4</a>	12	13	29	0,023
		8x10	NPT1/4	<a href="#">FBPL8/10-1/4</a>	14	16	30	0,031
		8x10	NPT3/8	<a href="#">FBPL8/10-3/8</a>	14	16	31	0,040
		10x12	NPT3/8	<a href="#">FBPL10/12-3/8</a>	14	17	33	0,040

## F3BPL Raccord droit, mâle BSPT




	Laiton nickelé 	<b>ØD</b>			<b>F</b>	<b>F1</b>	<b>H</b>	<b>kg</b>
		2,7x4	R1/8	<a href="#">F3BPL2.7/4-1/8</a>	10	8	20,5	0,009
		4x6	R1/8	<a href="#">F3BPL4/6-1/8</a>	10	11	23,5	0,016
		4x6	R1/4	<a href="#">F3BPL4/6-1/4</a>	14	11	26,5	0,025
		6x8	R1/8	<a href="#">F3BPL6/8-1/8</a>	12	13	23,5	0,015
		6x8	R1/4	<a href="#">F3BPL6/8-1/4</a>	14	13	26,5	0,023
		6x8	R3/8	<a href="#">F3BPL6/8-3/8</a>	17	13	27,6	0,026
		7,5x10	R1/4	<a href="#">F3BPL7.5/10-1/4</a>	14	16	27,5	0,031
		7,5x10	R3/8	<a href="#">F3BPL7.5/10-3/8</a>	17	16	28,6	0,037
		8x10	R1/4	<a href="#">F3BPL8/10-1/4</a>	14	16	27,5	0,031
		8x10	R3/8	<a href="#">F3BPL8/10-3/8</a>	17	16	28,6	0,043
		10x12	R3/8	<a href="#">F3BPL10/12-3/8</a>	17	17	30,1	0,036
		11x14	R3/8	<a href="#">F3BPL11/14-3/8</a>	19	22	32,5	0,058

## F4BPL Raccord droit, mâle BSPP

	Laiton nickelé 	<b>ØD</b>	<b>C</b>		<b>E</b>	<b>F</b>	<b>F1</b>	<b>H</b>	<b>kg</b>
		4x6	G1/8	<a href="#">F4BPL4/6-1/8</a>	8	14	11	26	0,021
		6x8	G1/4	<a href="#">F4BPL6/8-1/4</a>	9	17	13	28	0,030

Les raccords sont livrés avec un joint cuivre.


## F8BPL Raccord droit, mâle métrique

	Laiton nickelé 	<b>ØD</b>	<b>C</b>		<b>E</b>	<b>F</b>	<b>F1</b>	<b>H</b>	<b>kg</b>
		6x8	M10x1	<a href="#">F8BPL6/8M10</a>	7	14	13	28	0,021
		6x8	M12x1,25	<a href="#">F8BPL6/8M12</a>	7	17	13	28	0,024

Les raccords sont livrés avec un joint cuivre.

### Dimensions des tubes selon les filetages des écrous

D : diamètre du tube (mm)	C : filetage métrique	D1 : diamètre de passage (mm)	F : six-pans de l'écrou (mm)	H : longueur de pénétration du tube (mm)
2,7x4	M6x0,75	1,5	8	4,5
4x6	M9x0,75	3	11	6,5
6x8	M11x0,75	5	13	6,5
7,5x10	M13x1	6,5	17	7
8x10	M13x1	6,5	17	7
10x12	M15x1,25	9	17	7,5
11x14	M18x1,50	9,5	22	8,5



Raccords à canule PL en laiton nickelé